

## LYS011764WW - DMX Protocol

Revision: A

Valid from firmware version: 1.0

DMX mode		Name	DMX value		DMX percentage		Function	Default DMX Value
Standard (7ch)	Simplified (4ch)							
1	1	Intensity	0	255	0.0%	100.0%	No light → Full light	0(0%)
2			0	65535	0.0%	100.0%	Intensity fade, fine (LSB)	
3	2	Warm	0	255	0.0%	100.0%	No light → Full light	0(0%)
4			0	65535	0.0%	100.0%	Intensity fade, fine (LSB)	
5	3	Cold	0	255	0.0%	100.0%	No light → Full light	0(0%)
6			0	65535	0.0%	100.0%	Intensity fade, fine (LSB)	
7	4	Color temperature	0	17	0.0%	6.7%	No function	0(0%)
			18	34	7.1%	13.3%	3159K	
			35	51	13.7%	20.0%	3407K	
			52	68	20.4%	26.7%	3608K	
			69	85	27.1%	33.3%	3796K	
			86	102	33.7%	40.0%	4208K	
			103	119	40.4%	46.7%	4407K	
			120	136	47.1%	53.3%	4597K	
			137	153	53.7%	60.0%	4634K	
			154	170	60.4%	66.7%	4791K	
			171	187	67.1%	73.3%	5010K	
			188	204	73.7%	80.0%	5200K	
			205	221	80.4%	86.7%	5400K	
			222	238	87.1%	93.3%	5600K	
239	255	93.7%	100.0%	5800K				