

1500 II Beam - DMX Protocol

Revision: A

Valid from firmware version: 3.0

DMX mode			Name	DMX value		DMX percentage		Function	Default DMX Value					
Standard (25ch)	Simplified (23ch)	Extended (31ch)												
1	1	1	Strobe/Shutter	0	31	0.0%	12.2%	Closed	0(0%)					
				32	63	12.5%	24.7%	Open						
				64	127	25.1%	49.8%	Synchronous strobe from slow to fast						
				128	159	50.2%	62.4%	Open						
				160	223	62.7%	87.5%	Random strobe from slow to fast						
				224	255	87.8%	100.0%	Open						
2	2	2	Intensity	0	255	0.0%	100.0%	No light → Full light	0(0%)					
3	3	3		0	65535	0.0%	100.0%	Intensity fade, fine (LSB)						
4	3	4	Cyan	0	255	0.0%	100.0%	White → Full cyan	0(0%)					
				0	65535	0.0%	100.0%	Cyan fade, fine (LSB)						
5	4	6	Magenta	0	255	0.0%	100.0%	White → Full magenta	0(0%)					
				0	65535	0.0%	100.0%	Magenta fade, fine (LSB)						
6	5	8	Yellow	0	255	0.0%	100.0%	White → Full yellow	0(0%)					
				0	65535	0.0%	100.0%	Yellow fade, fine (LSB)						
7	6	10	CMY color macro	0	15	0.0%	5.9%	CMY color macro off	0(0%)					
				16	135	6.3%	52.9%	CMY synchronous color from slow to fast						
				136	255	53.3%	100.0%	CMY random color from slow to fast						
8	7	11	CTO	0	255	0.0%	100.0%	Warm → Cold	0(0%)					
				0	65535	0.0%	100.0%	CTO fade, fine (LSB)						
9	8	13	Color wheel	0	15	0.0%	5.9%	Open	0(0%)					
				16	31	6.3%	12.2%	Color 1						
				32	47	12.5%	18.4%	Color 2						
				48	63	18.8%	24.7%	Color 3						
				64	79	25.1%	31.0%	Color 4						
				80	95	31.4%	37.3%	Color 5						
				96	111	37.6%	43.5%	Color 6						
				112	127	43.9%	49.8%	Color 7						
				128	187	50.2%	73.3%	Color continuous rotation CW from slow to fast						
				188	195	73.7%	76.5%	Stop						
				196	255	76.9%	100.0%	Color continuous rotation CCW from slow to fast						
				10	9	14	Rotating gobo wheel 1	0		9	0.0%	3.5%	Open gobo	0(0%)
								10		19	3.9%	7.5%	Gobo 1	
20	29	7.8%	11.4%					Gobo 2						
30	39	11.8%	15.3%					Gobo 3						
40	49	15.7%	19.2%					Gobo 4						
50	59	19.6%	23.1%					Gobo 5						
60	69	23.5%	27.1%					Gobo 6						
70	79	27.5%	31.0%					Gobo 1 shake						
80	89	31.4%	34.9%					Gobo 2 shake						
90	99	35.3%	38.8%					Gobo 3 shake						
100	109	39.2%	42.7%					Gobo 4 shake						
110	119	43.1%	46.7%					Gobo 5 shake						
120	127	47.1%	49.8%					Gobo 6 shake						
128	187	50.2%	73.3%					Gobo wheel continuous rotation CW from slow to fast						
188	195	73.7%	76.5%					Stop						
196	255	76.9%	100.0%					Gobo wheel continuous rotation CCW from slow to fast						
11	10	15	Gobo rotating/positioning gobo wheel 1					0	127	0.0%	49.8%	Gobo rotation/positioning	0(0%)	
				128	187	50.2%	73.3%	Gobo continuous rotation CW from slow to fast						
				188	195	73.7%	76.5%	Stop						
				196	255	76.9%	100.0%	Gobo continuous rotation CCW from slow to fast						
12	16	0	65535	0.0%	100.0%	Gobo rotation/positioning, fine (LSB)								
13	11	17	Gobo wheel (static)	0	15	0.0%	5.9%	Open	0(0%)					
				16	23	6.3%	9.0%	Gobo 1						
				24	31	9.4%	12.2%	Gobo 2						
				32	39	12.5%	15.3%	Gobo 3						
				40	47	15.7%	18.4%	Gobo 4						
				48	55	18.8%	21.6%	Gobo 5						
				56	63	22.0%	24.7%	Gobo 6						
				64	71	25.1%	27.8%	Gobo 7						
				72	79	28.2%	31.0%	Gobo 1 shake						
				80	87	31.4%	34.1%	Gobo 2 shake						
				88	95	34.5%	37.3%	Gobo 3 shake						
				96	103	37.6%	40.4%	Gobo 4 shake						
				104	111	40.8%	43.5%	Gobo 5 shake						
				112	119	43.9%	46.7%	Gobo 6 shake						
				120	127	47.1%	49.8%	Gobo 7 shake						
				128	187	50.2%	73.3%	Gobo wheel continuous rotation CW from slow to fast						
				188	195	73.7%	76.5%	Stop						
196	255	76.9%	100.0%	Gobo wheel continuous rotation CCW from slow to fast										
14	12	18	Iris	0	255	0.0%	100.0%	Open → Close	0(0%)					
15	13	19	Iris macro	0	31	0.0%	12.2%	Disable Iris macro	0(0%)					
				32	63	12.5%	24.7%	Effect - Synchronous open from fast to slow						
				64	95	25.1%	37.3%	Effect - Synchronous off from slow to fast						
				96	127	37.6%	49.8%	Effect - Random open from slow to fast						
				128	159	50.2%	62.4%	Effect - Random off from fast to slow						
				160	191	62.7%	74.9%	Strobe follow from slow to fast						

				192	255	75.3%	100.0%	Disable Iris macro	
16	14	20	Focus	0	255	0.0%	100.0%	Near → Far	0(0%)
				0	65535	0.0%	100.0%	Focus, fine (LSB)	
17	15	22	Frost/Zoom	0	79	0.0%	31.0%	White → Full frost	0(0%)
				80	255	31.4%	100.0%	Narrow → Wide	
				0	65535	0.0%	100.0%	Zoom, fine (LSB)	
18	16	24	Prism	0	31	0.0%	12.2%	Off	0(0%)
				32	255	12.5%	100.0%	On	
19	17	25	Prism rotation	0	127	0.0%	49.8%	Prism indexed	0(0%)
				128	187	50.2%	73.3%	Prism continuous rotation CW from slow to fast	
				188	195	73.7%	76.5%	Stop	
				196	255	76.9%	100.0%	Prism continuous rotation CCW from slow to fast	
20	18	26	Pan	0	255	0.0%	100.0%	Pan	46(18.0%)
21	19	27		0	65535	0.0%	100.0%	Pan, fine (LSB)	
22	20	28	Tilt	0	255	0.0%	100.0%	Tilt	0(0%)
23	21	29		0	65535	0.0%	100.0%	Tilt, fine (LSB)	
24	22	30	Scan speed	0	255	0.0%	100.0%	Scan speed from fast to slow	0(0%)
25	23	31	Special controls	0	9	0.0%	3.5%	No function	0(0%)
				10	19	3.9%	7.5%	Open light after 5 seconds	
				20	29	7.8%	11.4%	Close light after 5 seconds	
				30	39	11.8%	15.3%	Color wheel half color switch	
				40	49	15.7%	19.2%	Color wheel random positioning	
				50	59	19.6%	23.1%	Reserved	
				60	69	23.5%	27.1%	Reset all motor after 5 seconds	
				70	79	27.5%	31.0%	Scan motor reset after 5 seconds	
				80	89	31.4%	34.9%	All color motor reset after 5 seconds	
				90	99	35.3%	38.8%	All gobo motor reset after 5 seconds	
				100	109	39.2%	42.7%	All strobe motor reset after 5 seconds	
				110	119	43.1%	46.7%	Other motor reset after 5 seconds	
				120	129	47.1%	50.6%	Built-in program 1	
				130	139	51.0%	54.5%	Built-in program 2	
				140	149	54.9%	58.4%	Built-in program 3	
				150	159	58.8%	62.4%	Built-in program 4	
				160	169	62.7%	66.3%	Built-in program 5	
				170	179	66.7%	70.2%	Built-in program 6	
				180	189	70.6%	74.1%	Built-in program 7	
				190	199	74.5%	78.0%	Built-in program 8	
200	209	78.4%	82.0%	Built-in program 9					
210	219	82.4%	85.9%	Built-in program 10					
220	255	86.3%	100.0%	Voice control					